⊘ AIPHONE

NE-NVP (-W)
## Vandal Proof Sub Station for NEM System
SBX-NVP
Surface Mount Box for NE-NVP

- INSTRUCTIONS -

The NE-NVP is a vandal proof sub station designed for use with the NEM system. The NE-NVP-W is the weather resistant model. It is constructed of 11 gauge carbon steel with a white powder-coated finish. The NE-NVP can be flush or surface mounted and includes tamper proof screws and tool for installation.

WIRING DIAGRAM:

NOTES:
1. Do not cut the green jumper on the circuit board unless a corridor lamp is included at the sub station.
2. NE-NVP flush mounts into a 3-gang masonry type box (Raco #692, 697, or equivalent.)
3. Surface mount box for NE-NVP is model SBX-NVP, sold separately.

SPECIFICATIONS:

Power Source:	Supplied by master station
Speaker:	20 ohms, 3" diameter, water proof and puncture resistant, 2.5 oz. ceramic magnet
Call Button:	Single pole, single throw (SPST), normally open (N/O)
Faceplate:	11 gauge carbon steel with powder-coated white baked epoxy finish
Call Annunciation:	Pressing call button at sub latches call at NEM master until answered
Communication:	Hands free at sub. Master is push-to-talk or VOX handset
Mounting Hardware:	Tamper proof screws
Terminations:	Color-coded prewired pigtails
Wiring:	2 conductors homerun; or 1 common plus 1 individual per sub, looped through each sub. Shielded cable is recommended. Use Aiphone #822202 or #821802 for homerun wiring, #822206 for up to 5 stations on each run, or #822210 for up to 9 stations on each run.
Wiring Distance:	420' with 22AWG; 1,000' with 18AWG.
Dimensions (H x W x D):	NE-NVP alone: 7-1/2" x 5-1/2" x 2". With SBX-NVP: 8-5/8" x 6-5/8" x 2-1/4"